

## DC-FEEDER (FME-male)

For use with active antennas 60101-000 and 60121-000

- DC-Feeder for feeding DC voltage through a long coaxial cable to an active antenna requiring DC power
- This DC-Feeder is compatible with Active Antennas P/N 60101-000 and 60121-000. For maximum voltage to the antenna please consult the data sheet for the corresponding antenna
- Compatible with SatTrans SAT-VDA Thuraya Hands-Free Car Kit, SatTrans SAT-DOCKER a.o.

### ELECTRICAL SPECIFICATIONS

Frequency	1525 - 1660.5 MHz (L-band)
Impedance	50 ohm
Satellite system	Thuraya
Supply voltage	Depending on actual antenna

### MECHANICAL SPECIFICATIONS

Color	Black
Mounting	Indoor
Materials	Technomelt, PVC, PE, PCB, brass and copper
Connector	N-female to antenna
Connector2	FME-male to terminal
Cable	For power supply: 1.5 m DC-wire
For Antenna Types	60101-000, 60121-000

### ORDERING INFORMATION

P/N	69003-001
-----	-----------

### PACKAGING INFORMATION

Type	Polybag
------	---------